

## SPARKULAR® WAVER

- \ 180 degree waving spark effect
- \Firing angle can be waving or any fixed direction between -90 to 90 degree
- \ Fast and precise nozzle waving based on exclusive dual PID algorithm control system
- \72 preset firing sequences, easy operation and programing
- Stainless steel housing, durable and reliable
- \ Motor status real time monitoring, safer to use and easier problem diagnosis
- \3.2" LCD color screen, user friendly

## **SPECIFICATIONS**

\ MODEL: BT84/BT85

\ DIMENSION: 300×290×273mm

\WEIGHT: 15.5kg

\VOLTAGE: 220V(BT84)110V(BT85), 50/60Hz

**\WORK POWER: 500W** 

\ HOUSING MATERIAL: 304 stainless steel \ MOTOR STATUS MONITORING: Yes

\COLOR SCREEN: Yes, 3.2"

\FIRING DIRECTION: Waving between -90° to 90°

Fixed firing angle between -90° to 90°

\ EFFECT ANGLE ADJUSTABLE: YES, -90° to 90°

\ PRESET FIRING SEQUENCES: YES, 72 preset firing sequences

\ HOPPER CAPACITY: 400g

\ INTERFACE: 3-pin and 5-pin XLR \ CONTROL: DMX, 6 channels

\ EFFECT HEIGHT: 2.5-4.5m adjustable

