

## U-CONFETTI BLOWER



uFetti Blower is a powerful confetti launcher with output up to 18m, equipped with dual fully automatic confetti dosing hopper and can be controlled both manually or automatically by DMX. Take advantage of the customized high-power blower and optimized Venturi tube design, the confetti can be spread farther and wider.

### Features

- ∨ Up to 18m confetti output
- ∨ Farther and wider confetti spread with customized high-power blower and optimized Venturi tube design
- ∨ Dual independently controllable hopper, automatic confetti dosing
- ∨ Adjustable output density and output angles
- ∨ Real-time motor running status monitoring
- ∨ Premium accessories, strong and durable
- ∨ Multi air inlet structure, machine keeps working even the air inlets on panel are blocked
- ∨ Rugged design with premium accessories, suitable for touring

### Specifications

#### Dimension

880 x 660 x 1295mm

#### Net Weight

112kg

#### Voltage

AC200-240V / AC100-120V, 50/60Hz

#### Work Power

2200W

#### Confetti Hopper

2, separate control of each hopper

**Hopper Capacity**

2kg paper confetti / hopper \*2; 4kg metallic confetti / hopper \*2

**Consumption Rate**

Paper confetti: 0.9kg/min; Metallic confetti: 1.8kg/min

**Interface**

3-pin and 5-pin XLR

**Control**

Manual, DMX, Wireless DMX (via 5-PIN DMX IN)

**Output**

Up to 18m

**Output Angles**

40°-90° (6 adjustable angles)

**Blower Speed Adjustable**

Yes (High/Low)

**Output Density Adjustable**

Yes

**LED Warning Light**

Yes

**Caster**

4 casters with brake

**Effect**